

Material SE DB list					
Red copper wire mesh					
Number	mesh size	SE in frequency(Db)			
		450KHz	50MHz	1GHz	10Ghz
1	40 mesh	105	80	50	30
2	100 mesh	110	85	55	37
3	200 mesh	120	100	63	43
Brass wire mesh					
Number	mesh size	SE in frequency			
		450KHz	50MHz	1GHz	10Ghz
1	40 mesh	103	78	48	28
2	100 mesh	107	82	53	35
3	200 mesh	113	92	59	40
Phosphor bronze wire mesh					
Number	mesh size	SE in frequency			
		450KHz	50MHz	1GHz	10Ghz
1	40 mesh	104	79	49	29
2	100 mesh	108	83	54	36
3	200 mesh	115	95	61	41
stainless steel wire mesh					
Number	Mesh size	SE in frequency			
		450KHz	50MHz	1GHz	10Ghz
1	40 mesh	102	77	47	31
2	100 mesh	106	80	51	37
3	200 mesh	112	90	58	45
Pure silver wire mesh					
Number	Mesh size	SE in frequency			
		450KHz	50MHz	1GHz	10Ghz
1	200 mesh	122	101	65	45